


Micro-Speed

Spec:

- Fully Proportional Brake and Reverse Control
- Input Voltage: 4-8 cells
- Max. Current: 10 Amp
- Weight: 11g
- Size: 22.7 x 22.5 x 5.9 mm



Installation:



NEVER connect a Schottky diode to a reverse speed control !

Radio Setup:

- [1] Turn on your transmitter and set all throttle rates to 100%.
- [2] Connect the speedo to the battery. Do not move the throttle on your transmitter.
- [3] Press the Setup button on your speedo until the LED will go out.
- [4] After the LED will come on give full throttle, full reverse and then back to neutral on your transmitter.

The speedo is now tuned to your transmitter. To check you have tuned it properly, the LED will only come on at neutral, full speed and full brake. If your speedo is not set properly, please check if your throttle rates is set to 100% !

Warning:


- Do not allow water or moisture into the unit.
- Never run motor on external battery when hooked up on speedo.
- Never short unit, no reverse voltage.

Technische Daten:

- Intelligente Bremse und Rückwärtsfahrt
- Zellenanzahl: 4-8 Zellen
- Max. Strom: 10 Amp
- Gewicht: 11g
- Abmessungen: 22.7 x 22.5 x 5.9 mm



Anschluß:



Schließen Sie niemals eine Schottky Diode an einem Rückwärtsregler an !

Einstellen auf den Sender:

- [1] Schalten Sie den Sender ein und stellen Sie den maximalen Gasweg auf 100%.
- [2] Schliessen Sie den Regler an Ihren Akku an. Bewegen Sie den Gashebel Ihres Senders nicht.
- [3] Drücken Sie die Setup-Taste des Regler's bis die LED erlischt.
- [4] Wenn die LED wieder leuchtet geben Sie Vollgas, Vollbremse und gehen zurück in die Neutralstellung des Senders.

Ihr Regler ist fertig eingestellt. Bei richtiger Einstellung leuchtet die LED bei Neutral, Vollgas und Vollbremse. Stimmen die Einstellungen nicht, kontrollieren Sie ob der Gasweg korrekt eingestellt ist.

Warnung:

- Verpolen Sie den Regler nicht.
- Lassen Sie Ihr RC-Modell niemals unbeaufsichtigt, solange ein Akku angesteckt ist.
- Nicht für Kinder unter 14 Jahre, kein Spielzeug!

Robitronic Electronic Ges.m.b.H.

Tel.: +43-1-982 09 20 * Fax: +43-1-982 09 21
Em@il: info@robitronic.com * <http://www.robitronic.com>